

ARTICULIGHT

15-06 Morlot Avenue, Fair Lawn, NJ 07410 USA Tel: (201) 796-2690 Fax: (201) 796-8818

info@articulight.com

articulight@aol.com

www.articulight.com

LED SERIES

SRC-174P CONTROLLER



- * 192 DMX channels
- * 12 scanners of 16 channels each
- * 30 banks of 8 programmable scenes
- * 6 programmable chase of 240 scenes each
- * 8 slider for manual control of channels
- * Assignable joystick for ease movement
- * File dump allows data to be sent or received between two units
- * Auto mode program controlled by speed and fade time sliders
- * Fade time/ assign fade time
- * Reversible DMX channels fixture to react in opposition to others in a chase
- * 8 channel or 16 channel mode
- * Fine adjustment for joystick pan and tilt
- * Blackout master button
- * Manual override button allow you to grab any fixture on the fly
- * Built in microphone for music triggering
- * MIDI control over banks, chases and blackout
- * DMX polarity selector
- * Power failure memory
- * Fog machine connector
- * Power input: DC 9-12V 300ma min
- * Audio input: by buit-in microphone or line in, 100mv-1vpp
- * DMX in/out: 3 pin male/female XRL
- * MIDI in: 5 pin male/female XRL
- * MIDI in: 5 pin multiple socket
- * Dimensions (mm): L516 x W160 x H90
- * Weight: 2.7kg

DUE TO CONTINUOUS IMPROVEMENTS, SPECIFICATIONS MAY CHANGE WITHOUT PRIOR NOTICE.